


**Manufacturer** Prescolite  
**Model** MD8LED6L35K8120V2DM  
**Description** 8" downlight  
**Driver** Lutron Hi-lume A-Series (x2)  
**Nominal Power (W)** 90  
**Dimming Control** Forward- and reverse-phase  
**Product Range**  
**Test Date** 8/26/2015

Dimmer Tested Against:	SDM12-EM	EDIMMOD	
Pass/Fail	Pass	Pass	
<b>Best-Fit Power Profile:</b>			
Minimum ON	22	10	
Maximum ON	83	81	
Adjust	0	0	
<b>Light Output Range (vs. non-dimmed)</b>			
Maximum (Perceived)	95.8%	96.0%	
Minimum (Perceived)	9.9%	9.9%	
Minimum (Measured)	1.0%	1.0%	

**Linearity Curves (Best-fit Power Profile Applied):**



**Observations:**

Raising the Minimum On to 22 (forward-phase) assures that the light will come on when turned on to low dim level, without sacrificing low-end light output, due to a relatively flat low-end curve.