Llegrand[®]

Manufacturer B	ulbrite						
Model #772734							
Description PAR30L							
Driver Integrated							
Nominal 13							
Power (W)							
Dimming Forward		and					
Control Reverse Ph		ase					
Product -							
Range							
Test Date 4/16/2018							
Dimmer Tested		SDM12-	SCP	UDM-	UDM-	UDS-	UDS-
Against:		EM		FWD	REV	F	R
Pass/Fail		Pass	Pass	Pass	Pass	Pass	Pass
Best-Fit Power Profile:							
Minimum ON		1	3	3	5	3	3
Maximum ON		74	76	74	68	79	60
Adjust		100	100	100	100	95	100
Light Output Range (vs. non-dimmed)							
Maximum (Perceived), 120V		95.3%	95.4%	95.1%	95.4%	95.1%	95.2%
Minimum (Perceived)		12.3%	17.7%	18.6%	27.4%	15.1%	29.9%
Minimum (Measured)		1.5%	3.1%	3.5%	7.5%	2.3%	8.9%
Linearity Curves (Best-fit Power Profile Applied):							

Perceived Intensity (Percent) 🔶 Ideal SDM12-EM ------ScenePoint 📥 UDM-FWD WDM-REV -UDS-F UDS-R Programmed Level (Percent)

Observations:

bgk