Manufacturer	Halo		
Model	HU1048D927P		
Description	Light Bar		
Driver	3105DC		
Nominal Power (W)	20		
Dimming Control	Forward Phase		
Product Range	-		
Test Date	8/7/2017		

Dimmer Tested Against:	SDM12-EM	ScenePoint	UDM-FWD
Pass/Fail	Pass	Pass	Pass
Best-Fit Power Profile:			
Minimum ON	6	7	7
Maximum ON	81	85	85
Adjust	5	10	10
Light Output Range (vs. non-dimmed)			
Maximum (Perceived), 120V	95.6%	95.7%	95.6%
Minimum (Perceived)	16.3%	15.7%	15.7%
Minimum (Measured)	2.6%	2.5%	2.5%

Perceived Intensity (Percent) -Ideal SDM12-EM ScenePoint UDM-FWD **Programmed Level (Percent)**

Linearity Curves (Best-fit Power Profile Applied):

Observations:

bgk